

Tesi portable ignition devices are designed to ignite burners without an individual pilot torch or electrode assembly. They are the best back up solution to solve existing igniters failures or in case of emergency. Thanks to a solid design and low voltage input, the operator can handle the rod quite easily during maintenance, without any risk of breaking the insulators and avoiding dangerous electric shocks.

XE 18 PB 06

- THEY DON'T NEED TO BE LINKED TO THE MAIN POWER SUPPLY
- INTERNAL 12 V 7.2 Ah RECHARGEABLE BATTERY
- BUILT-IN AUTOMATIC CHARGER
- HIGH ENERGY SPARK GENERATED
- THEY ARE SUITABLE TO IGNITE ALL KINDS OF FUEL EVEN IN TOUGH APPLICATIONS

XE 18 PB 06 TECHNICAL DATA

POWER SUPPLY UNIT	
INPUT VOLTAGE	12 VDC
OUTPUT ENERGY (PER SPARK)	18 J
SPARK FREQUENCY	4 sparks/second

ENCLOSURE	
PROTECTION CLASS	IP65
MATERIAL	aluminium alloy
OPERATING TEMPERATURE	-20°C ÷ +50°C
DIMENSIONS	344 x 272 x 110 mm
WEIGHT	5,7 kg

BATTERY CHARGER	
INPUT VOLTAGE	115 or 230 Vac 50 Hz
RECHARGE OUTPUT VOLTAGE	13,5 VDC

IGNITER	
MATERIAL	stainless steel
OPERATING TEMPERATURE	760°C (max 1000°C)
WEIGHT	0.8 Kg per meter of length
LENGTH	customizable, according to specifications
TIP	High Energy, easily replaceable 17 mm (12/14 mm on request)
HANDLE	rubber, 150 mm as standard, 90° on request
OPTIONAL	adjustable stopping flange

CONNECTION CABLE	
MATERIAL	flexible stainless armoured cable
FITTINGS	bend or straight
OPERATING TEMPERATURE	-60°C ÷ +180°C (200°C for short time)
WEIGHT	0.4 Kg per meter of length
LENGTH	customizable, according to specifications

data subject to change without notice



NOTE:

In case of frequent use, you can leave the charging circuit connected to the mains power supply (115 / 230VAC), in Not Classified Areas, provided you keep the 1/2" gas evacuation cap completely open. Once maximum charge is reached, the charger will provide an appropriate holding current. After repositioning the cap and the charging cable, you have an ignition system always ready for use. If you're leaving the device unused for an extended period of time or in case of storage, disconnect the battery from the electronic circuit.